

Bluetooth Digital Fingertip Pulse Oximeter

The new fingertip pulse oximeter with bluetooth offers a smart, reliable and precise way to check Oxygen Saturation (SpO₂), Pulse Rate, and Perfusion Index, for both adults and paediatrics

EASY TO USE: One button operation. Continuous measurement of SpO₂, PR, PI, pulse bar and displayed waveform

BLUETOOTH: Automatically synchronises readings to a linked smart phone. App can be downloaded for free, supporting both Android and Apple iOS devices

RELIABLE & ACCURATE: Blue and yellow dual colour OLED screen, four direction display

ENERGY SAVING & ENVIRONMENTAL PROTECTION: Audible and visual alarm with low battery indication. Automatic switch off after 8 seconds to save battery life. Over 40 hours of continuous use on 2 x AAA batteries

FDA 510(k) CLEARED & CE CERTIFIED



CE 0123 FDA 510(k)



Product Details

- **Transducer:** Dual-wavelength LED sensor
- **SpO₂ Measuring Range:** 35%-100%
- **SpO₂ Measuring Accuracy:** ≤ 2% range from 70% to 100%
- **SpO₂ Default Alarm Limit:** Low limit – 90%
- **Pulse Measuring Range:** 30 bpm-240 bpm
- **Pulse Measuring Accuracy:** ±2 bpm or ±2% whichever is greater
- **Pulse Rate Default Alarm Limit:** High limit – 120 bpm, Low limit – 50 bpm
- **Perfusion Index (PI):** 0%-20%
- **Battery Requirements:** 2 x 1.5V AAA batteries

Code	Description	Units per box
PC60FW	Bluetooth Digital Fingertip Pulse Oximeter	1

Please see the Instructions for a complete listing of the indications, contraindications, warnings and precautions.

The symbol ® indicates the trademark is registered in the U.S. Patent and Trademark Office and certain other countries. © Copyright 2020, Amsino International, Inc. All rights reserved.